



## **Digital Output Modules, 6ES7222-1BF32-0XB0**

URL:<https://www.sxplc.com/digital-output-modules-6es7222-1bf32-0xb0>

### **Product data sheet**

SIMATIC S7-1200, Digital output SM 1222, 8 DO, 24 V DC, transistor 0.5 A

<b>General information</b>	
Product type designation	SM 1222, DQ 8x24 V DC/0.5 A
<b>Supply voltage</b>	
permissible range, lower limit (DC)	20.4 V
permissible range, upper limit (DC)	28.8 V
<b>Input current</b>	
from backplane bus 5 V DC, max.	120 mA
<b>Power loss</b>	
Power loss, typ.	1.5 W
<b>Digital outputs</b>	
Number of digital outputs	8
• in groups of	1
Short-circuit protection	No; to be provided externally
Limitation of inductive shutdown voltage to	typ. (L+) -48 V
<b>Switching capacity of the outputs</b>	
• with resistive load, max.	0.5 A
• on lamp load, max.	5 W
<b>Output voltage</b>	
• Rated value (DC)	24 V
• for signal "0", max.	0.1 V; with 10 kOhm load
• for signal "1", min.	20 V DC
<b>Output current</b>	
• for signal "1" rated value	0.5 A
• for signal "0" residual current, max.	10 µA
<b>Output delay with resistive load</b>	
• "0" to "1", max.	50 µs
• "1" to "0", max.	200 µs
<b>Total current of the outputs (per group)</b>	
horizontal installation	
— up to 50 °C, max.	4 A; Current per mass
<b>Cable length</b>	
• shielded, max.	500 m
• unshielded, max.	150 m

